



Universal Update Manager Guide

EPP 8.3

www.seqrite.com



Copyright Information

Copyright © 2008–2024 Quick Heal Technologies Ltd. All Rights Reserved.

No part of this publication may be reproduced, duplicated, or modified in any form or incorporated into any information retrieval system, electronic or any other media or transmitted in any form without prior permission of Quick Heal Technologies Limited, Marvel Edge, Office No.7010 C & D, 7th Floor, Viman Nagar, Pune 411014, Maharashtra, India.

Marketing, distribution or use by anyone barring the people authorized by Quick Heal Technologies Ltd. is liable to legal prosecution.

Trademarks

Seqrite and DNAScan are registered trademarks of Quick Heal Technologies Ltd. while Microsoft and Windows are registered trademarks of Microsoft Corporation. Other brands and product titles are trademarks of their respective holders.

License Terms

Installation and usage of Seqrite Endpoint Security is subject to user's unconditional acceptance of the Seqrite end-user license terms and conditions.

To read the license terms, visit <http://www.seqrite.com/eula> and check the End-User License Agreement for your product.

Contents

- Overview 2**
- Audience 2**
- System Requirements for EPP and EDR Update Manager 3**
 - EPP Update Manager3
 - EDR Update Manager.....3
- Installation Steps 4**
- Uninstallation Steps..... 4**
- Configuration (suumconfig.json) 5**

Overview

Seqrite Universal Update Manager is a standalone tool that is used to download and manage the updates for different Seqrite products with different types of updates. It provides you the flexibility to download the updates on a single machine for Seqrite products. This tool can be deployed on any platform and provides the update functionality for the different endpoints.

Audience

This guide is useful for the Seqrite Admin, SOC Managers, and Analysts who would be using the system.

System Requirements for EPP and EDR Update Manager

EPP Update Manager

Server that supports up to 1 to 2000 endpoints

- Ubuntu 22.04
- Available Disk Space: 8 GBs or above
- Available RAM: 8 GBs or above
- Processor: 4 Core (x86-64), 2.60GHz or above

Server that supports up to 15000 endpoints

- Ubuntu 22.04
- Available Disk Space: 8 GBs or above
- Available RAM: 16 GBs or above
- Processor: 8 Core (x86-64), 2.60GHz or above

Server that supports up to 25000 endpoints

- Ubuntu 22.04
- Available Disk Space: 8 GBs or above
- Available RAM: 32 GBs or above
- Processor: 16 Core(x86-64), 2.60GHz or above

Note: Set server upper limit (ulimit) higher than the derived number of connections; recommended to be 100000.

EDR Update Manager

Supported Platforms	CPU	Memory	Disk
<ul style="list-style-type: none">• Linux Mint 19.2• Linux Mint 20 64bit• Ubuntu 22• Ubuntu 20.04 64bit• openSUSE 42.3, 15.2 64bit• Red Hat Enterprise Linux 9.1• BOSS 6 32bit• BOSS 8 64bit• Rocky Linux	2 Core	4 GB	50 GB

Installation Steps

1. Download Update Manager installer from the following location:

OPE:

<https://dlupdate.quickheal.com/builds/seqrite/cai/suum/installer/eng/SUUMunix64.zip>

EPS 8.2:

https://dlupdate.quickheal.com/builds/seqrite/cai/suum/eps/1_1_0/eng/SUUMunix64.zip

EPS 8.3:

https://dlupdate.quickheal.com/builds/seqrite/cai/suum/eps/1_2_0/eng/SUUMunix64.zip

2. Follow these steps to install the Update Manager.
 1. Put UM installer SUUM_unix_amd64.sh and **suumconfig.dat** together.
 2. Check **SUUM_unix_amd64.sh** permissions for execution.
 3. Use the command **sudo ./SUUM_unix_amd64.sh** to install Update Manager.

The installation paths is: /usr/lib/Seqrite/UpdateManager/.

Note: On some of RHEL, CentOS, Scientific Linux, Rocky Linux and Alma Linux systems SELinux is in enforcing mode. For Update Manager installation we need to change it to permissive mode using the command.

Post Installation Steps

1. Check if the Update Manager server(umservice) is responding on the default configured port (18081) with the below mentioned command:

```
sudo lsof -i:18081 | grep LISTEN
```

2. If not, please re-configure a new free port using below mentioned Update Manager command:

```
./umcli service-config --action=set --serverPort=<new_port>
```

Uninstallation Steps

Follow these steps to uninstall the Update Manager.

1. Navigate to installation directory.
2. Run **sudo ./uninstall**.

Configuration (suumconfig.json)

(Note that these configurations are converted into a dat file and then is consumed by the Update Manager.)

```
{
  "tenantID": "1sWTAn",
  "packageID": "",
  "locale": "en",
  "brandName": "Seqrite",
  "installationPath": "/usr/lib/",
  "updateProxyURL": "http://<USERNAME>:<PASSWORD>@<IP>:<PORT>",
  "fileServerPort": "18081",
  "socketPort": "45835",
  "downloadRLkpbs": 4096,
  "products": {
    "EDR": {
      "updates": {
        "prdUpdate": {
          "downloadMode": 1,
          "downloadresume": true,
          "inetimeout_sec": 1000,
          "urllist": ["http://172.18.38.39:8080/"],
          "ScheduleTime": ""
        }
      }
    }
  },
  "EPS": {
    "updates": {
      "quickup": {
        "downloadMode": 0,

```


3	service-config	--action=get	Get current configuration for Update Manager.	./umcli service-config --action=get
4	service-config	--action=set --proxy=<proxyurl> --serverPort=<port> --download-rate=<inkbps>	Set Update Manager service parameters (proxy, serverPort, download rate). Given parameters are not compulsory.	./umcli service-config --action=set --proxy=""http://<USERNAME>:<PASSWORD>@<IP>:<PORT>" serverPort=8085 download-rate=1000
5	product-config	--action=getall	Retrieve configuration for all products	./umcli product-config --action=getall
6	product-config	--action=add --prdid=<product-name> --file=<input.json>	Add a new product configuration. Keep input.json into install dir with given format: <pre>{ "updates":{ "quickup" :{ "downloadMode": 0, "downloadresume": true, "inetimeout_sec": 10000, "urllist": [], "ScheduleTime": "" } } }</pre>	./umcli product-config --action=add --prdid=EDR --file=input.json
7	product-config	--action=remove --prdid=<product-name> --updatetype=<update-type>	Remove configuration of update type for the given product.	./umcli product-config --action=remove --prdid=EDR --updatetype=quickup
8	rollback-update	--prdid=<Product Name>	Rollback a previously applied update for the specified product.	./umcli rollback-update --prdid=EDR
9	get-status	--prdid=<Product Name>	Retrieve the status of the specified product.	./umcli get-status --prdid=EDR
10	update-schedule	--prdid=<product-name> --updatetype=<update-type> --schtime=<schedule in cron format>	Schedule an update for the specified product.	./umcli update-schedule --prdid=EDR --updatetype=prdUpdate --schtime="*/4 * * * *
11	update-schedule	--prdid=<product-name> --updatetype=<update-type> --schtime=""	Delete schedule for given update type of product.	./umcli update-schedule --prdid=EDR --updatetype=prdUpdate --schtime=""

12	get-reports	--prdid= <product-name> --updatetype= <update-type>	Retrieve and update reports for the specified product and update type.	./umcli get-reports --prdid=EDR --updatetype=prdUpdate
13	save-report	--srcfile= <report filename> --destfile= <full-path-with-name>	Save an updated report.	./umcli save-report --srcfile=SHHprdUpdate2024-02-17T11-00-55.354.rpt --destfile= <tmp file location>
14	display-report	--file= <report filename>	Display a saved update report.	./umcli. display-report: --file= <= <tmp file location>

SUUM File Server

This is a local file server to host downloaded updates by Update Manager.

File server will deploy on same machine on UM service start and map to the file-server directory inside installation folder.

Port for this server is provided at the following location:

- suumconfig.dat : <http://<IP/host>:18081/file-server>

To create directory structure for multiproduct updates on File Server follow below template:

Installation Directory

```
└─ file-server
    └─ EDR
        │ └─ prdUpdate
        │ │ └─ checksum.json
        │ │ └─ master.bin
        │ └─ updateType2
    └─ EPS
        └─ quickup
└─ 1800
└─ Build
```

Note: For EPS above hierarchy is by default available.